

Laser "1" Opaque Laser Transfer Paper

for **Dark Colors**

Before you begin

Designed for use in most newer technology oil and oil-less laser copiers and printers. Keep paper out of high humidity and away from moisture. Recommended for use on dark colored cotton, cotton/poly blends, and synthetics.

Printing Instructions

1. Preparing Image

- Set printer to heavy paper mode.
- Do NOT Mirror/Reverse the image.
- Print the image on the rough side of the transfer paper. (Not the side with the text.)
- Paper should be fed into copier/printer with the short dimension first. (grain long) using the bypass tray.
- Single-sheet feeding recommended.

2. Cut-out Design

- For best results trim away the unprinted paper around image.

3. Peel off Grid Backing Paper Before Pressing!

- This is done by gently peeling the backing apart from the polymer containing image.

Transferring Instructions

1. Pressing Transfer:

Heat Press Application

- Prepare heat press at 350 degrees F.
- Position fabric on press.
- Do NOT pre-press.
- Place heat transfer paper with image **facing UP** in desired position on fabric.
- Cover** imaged transfer with silicon paper. For a glossy finish, use teflon cover.
- Using above recommended temperature, apply medium pressure for 15-20 seconds. (Reduce time if using Dazzle-Trans with application.)



2. Peel & Wear

- Allow silicon sheet to cool completely. Then remove from garment.

Before Washing

Leave finish item for at least 24 hours before wash. Wash inside out in cold water. Dry at normal heat settings. Do not use bleach, fabric softener, or harsh detergents. Do not iron directly over transfer.

IMPORTANT: We thoroughly test each of our products on various substrates using different transfer equipment. However, it is impossible for us to duplicate all variables using all substrates and transfer equipment. Therefore, it is essential that you test the paper prior to production using your equipment, methods, and substrate material. Heat presses vary in accuracy. Conduct tests to determine the best time and temperature to use with your equipment. Please keep in mind that the Seller's and Manufacturer's maximum obligation shall be to replace any paper that has proven to be defective. Neither the Seller nor the Manufacturer shall be liable for injury, direct or consequential, arising out of the use of, or inability to use the paper.